

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://optosky.nt-rt.ru/> || otp@nt-rt.ru

Малошумящий спектрометр АТР3040 без охлаждения АТР3040 Un-cooled Low-noise Spectrometer



- Optosky ATP3040 is a low-noise, high-resolution, uncooled spectrometer. It employs 4096pixels CCD sensor spectral response covering UV to NIR wavelength. Readout speed reaches up to 10MHz, low noise signal process circuit, and fast and accurate spectral data collection.
- ATP3040 supplies power directly via USB port and output data via USB2.0/UART, and it's convenient to apply integration.
- ATP3040 has free SDK for customers self-developed, Optosky support C++, C#, Labview and Linux system SDK, which is very convenient for OEM customers to design solutions.

OPTICAL PARAMETER

Optical Resolution	0.06-2 nm (decide on slit and spectral range)
Incident Interface	SMA905 connector or free space
Dynamic Range	10000:1
Confocal Distance	77.5 mm for incidence / 112 mm for output
Numerical Aperture	0.11
Working Humidity	< 90%NC
Trigger	YES/IN and OUT

OPTICAL PARAMETER

Cooling Temperature	uncooled
Full Well	NA
Scanning Rate	< 1 kfps
Wavelength Range	350-800nm, 200-400nm, 200-850nm, 200-1000nm, 600-1000nm, 800-1000nm （available in custom wavelength）

DETECTOR

Detector Type	Linear CCD sensor
Effective Pixels	4096pixels
Pixels Dimension	7μm×200μm
Detector Model	Hamamatsu S13496
Sensitivity	1300(V/lx.s)
Dark Noise	8.3RMS@25℃

OPTICAL CONFIGURATION

Optical Design	Cross C-T
Incident Slit	5,10,25,50,100,150,200 μm (optional), available in custom width)

RAMAN SPECTROMETER DETECTOR

Detector Power Supply	DC 5V±10%
-----------------------	-----------

PHYSICAL PARAMETERS

Dimension	170×110×52 mm3
Weight	0.38kg
Sealing	Anti-sweat

ELECTRICAL PARAMETER

Integration Time	1 ms - 80 s
------------------	-------------

OPTICAL PARAMETER

Operating Current	<350 mA (uncooled) , <3.0A (cooled)
Storage Temperature	-30°c to + 70 °c
Operating Temperature	-10°c to + 50°c

FIELD SPECTRORADIOMETER

SNR	>1000 : 1
-----	-----------

Архангельск (8182)63-90-72 Астана (7172)727-132 Астрахань (8512)99-46-04 Барнаул (3852)73-04-60 Белгород (4722)40-23-64 Брянск (4832)59-03-52 Владивосток (423)249-28-31 Волгоград (844)278-03-48 Вологда (8172)26-41-59 Воронеж (473)204-51-73 Екатеринбург (343)384-55-89 Иваново (4932)77-34-06	Ижевск (3412)26-03-58 Иркутск (395)279-98-46 Казань (843)206-01-48 Калининград (4012)72-03-81 Калуга (4842)92-23-67 Кемерово (3842)65-04-62 Киров (8332)68-02-04 Краснодар (861)203-40-90 Красноярск (391)204-63-61 Курск (4712)77-13-04 Липецк (4742)52-20-81	Магнитогорск (3519)55-03-13 Москва (495)268-04-70 Мурманск (8152)59-64-93 Набережные Челны (8552)20-53-41 Нижний Новгород (831)429-08-12 Новокузнецк (3843)20-46-81 Новосибирск (383)227-86-73 Омск (3812)21-46-40 Орел (4862)44-53-42 Оренбург (3532)37-68-04 Пенза (8412)22-31-16	Пермь (342)205-81-47 Ростов-на-Дону (863)308-18-15 Рязань (4912)46-61-64 Самара (846)206-03-16 Санкт-Петербург (812)309-46-40 Саратов (845)249-38-78 Севастополь (8692)22-31-93 Симферополь (3652)67-13-56 Смоленск (4812)29-41-54 Сочи (862)225-72-31 Ставрополь (8652)20-65-13	Сургут (3462)77-98-35 Тверь (4822)63-31-35 Томск (3822)98-41-53 Тула (4872)74-02-29 Тюмень (3452)66-21-18 Ульяновск (8422)24-23-59 Уфа (347)229-48-12 Хабаровск (4212)92-98-04 Челябинск (351)202-03-61 Череповец (8202)49-02-64 Ярославль (4852)69-52-93
Киргизия (996)312-96-26-47	Россия (495)268-04-70	Казахстан (772)734-952-31		

https://optosky.nt-rt.ru/ || otp@nt-rt.ru